

PNWB





Function Alternative control of two pumps.

Selection modes: Stop - automatic - manual.

Operating principle Switches in 0 position: No operation is possible.

Switches in MAN position (push-button): The relay related to each switch remains operated whenever the switch is pushed, with independece of the state of the level.

Switches in AUTO position: When the liquid reaches the maximum level, relay 1 operates and releases when the liquid goes under the minimum level. If while relay 1 is operated the liquid reaches the alarm level, relay 2 operates and both relays release when the liquid goes under the minimum level. Relays 1 and 2 operate alternatively each time that the liquid reaches the maximum level.

If one of the switches goes to the 0 position, the alternate cycle is cancelled, and only operates the relay related to the switch in the AUTO position.

Switches in MAN or AUTO position: If the external thermal protector (safety device) detects a failure, whichever operation of the related relay is switched off and no-one operation is possible, the alternate cycle is cancelled and only operates the relay related to the thermal protector which did not detect the failure.

See more operating possibilities in the next page


Sensors Any level sensor with potential free contacts.


Contacts Two relays SPST NO (8 A).


Indications leds Power on (green) - Relays on (red) - Levels (yellow) - Safety devices (red)

		HOUSING		FUNCTION		OUTPUT		SUPPLY	
9							024	24 VAC	
							048	48 VAC	
Referen	Р	Plug-in	NW	Double level	В	B 2 SPST NO	110	110125 VAC	
							230	220240 VAC	
							400	380415 VAC	

To compose the reference, select one option of each column. Example: PNVB 048







Operating exceptions

There are some exceptions to the normal operating mode. Basically, they consist in the following ones:

- Pumps work in manual mode although level is under minimum.
- If any electrode fails during operation, the pumps work until the level goes below the deeper electrode which doesn't fail.

The complete set of exceptions are stated in the following true table. The "X" means that the pump works or not depending on the alternative cycle.


The signs "0»1" or "1»0" mean a change of state during a certain operation.

Pos	MIN	BAAV		TERMIC PROTEC.		AUTO		MANUAL	
Pos	MIIN	MAX	ALARM	1	2	RELAY1	RELAY 2	RELAY1	RELAY 2
1	0	0	0	1	1	0	0	1	1
2	1	0	0	1	1	0	0	1	1
3	0	1	0	1	1	Х	X	1	1
4	1	1	0	1	1	Х	Х	1	1
5	0	0	1	1	1	1	1	1	1
6	1	0	1	1	1	1	1	1	1
7	0	1	1	1	1	1	1	1	1
8	1	1	1	1	1	Х	Х	1	1
9	0	0	0	0	0	0	0	0	0
10	1	0	0	0	0	0	0	0	0
11	0	1	0	0	0	0	0	0	0
12	1	1	0	0	0	0	0	0	0
13	0	0	1	0	0	0	0	0	0
14	1	0	1	0	0	0	0	0	0
15	0	1	1	0	0	0	0	0	0
16	1	1	1	0	0	0	0	0	0
17	1	1	0	1»0	1	1»0	0»1	-	-
18	1	1	0	1	1»0	0»1	1»0	-	-

Supply		AC			
		PNWB			
	Galvanic isolation	Yes			
	Frequency	50 / 60 Hz			
	Operating margins	±1015%			
	Positive	-			
	Protected polarity	-			

		PNWB				
	Voltage phase-neutral	300 V				
	Overvoltage category	III				
	Rated impulse voltage	4 kV				
data	Pollution degree	2				
9	Protection	IP 20 B				
nta	Approximate weight	250 g				
anviromental	Storage temperature	-50+85°C				
ir	Operating temperature	-20+50°C				
anv	Humidity	3085% HR				
þ	Housing	Cycoloy - Light grey				
a	Socket	Lexan - Light grey				
×	Visor leds	Lexan - Transparent				
Constructive and	Button, terminal block, clip	Technyl - Dark blue				
str	Pins of the socket	Nickel-plated brass				
Š	Pins of the terminal block	-				
0	Approvals	Designed and manufactured under EEC standards. Electromagnetic compatibility , directives 89/ 366/EEC and 92/31/EEC. Electric safety, directive 73/23/EEC. Plastics: UL 91 V0				

			PNWB			
			5 6 7 4 2,5 A 8 3 2 1 10			
	Resistive load	AC	8 A / 250 V			
		DC	0,25 A / 200 V			
ıys			8 A / 24 V			
Output relays	Inductive load	AC	2,5 A / 250 V			
Ħ		DC	4 A / 24 V			
utp	Me	echanical life	> 30 x 10 ⁶ operations			
ō	Max. switching	rate, mech.	72.000 operations / hour			
	Electrical life	e at full load	360 operations / hour			
	Con	tact material	AgNi 90/10			
	Maxir	mum voltage	440 VAC			
	Opera	ating voltage	250 VAC			
	Volt. between	changeovers	2500 VAC			
	Voltage between	een contacts	1000 VAC			
	Voltage	coil/contact	5000 VAC			
	Distance	coil/contact	10 mm			
	Isolatio	n resistance	$> 10^4 \mathrm{M}\Omega$			



 $Rev.\ 02/00\cdot 07/05/10\cdot DISIBEINT\ reserves\ the\ right\ to\ modify\ the\ specifications\ stated\ in\ this\ document\ without\ previous\ notice$









